

LED DIMMER CONTROLLER

AL-3200 dimmer controller is an intelligent dimmer system specially designed for LED lighting. It adopts the most advanced digital brightness-adjusting technology that enables you to adjust the brightness via the control knob and can also adjust the brightness via the infrared remote control. It is suitable for installation in commercial and domestic lighting applications.



ProductCode	WiFi-102
Input Voltage	12 - 48V DC
Output Current	6A Max
Output Power	72W @ 12V - 288W @ 48V
Control Distance	30M Metres Max
Weight	200g
Ambient Temp Range	-20°C~+50°C
Output Signal	CV PWM
Grey Scale	1024 Levels
Dimming Range	0 - 100 %
Package size	L96 x W91 x H61

Sign	Button	Description
	ON/OFF	<ul style="list-style-type: none"> Turn on or turn off the LED lamp Any button can start the LED lamp at off status.
	DELAY OFF	<ul style="list-style-type: none"> Press this button, it will wait 30 seconds before turning off the light automatically.
	BRT+ BRT-	<ul style="list-style-type: none"> Press this two buttons to increase and decrease LED brightness. Can change brightness continuously by holding on the button.
	BRIGHTNESS KEYBOARD SHORTCUTS	<ul style="list-style-type: none"> Can select different brightness you want directly and immediately by Pressing these 4 shortcuts.
	DIY SCENE KEY	<ul style="list-style-type: none"> Total four keys, press any key over 3 seconds until the indicator flicks, it means the current brightness was recorded to this button, later you can enter this mode by just once pressing.

